

TOSHIBA TRANSISTOR SILICON NPN EPITAXIAL PLANAR TYPE

MT6L04AT

VHF~UHF BAND LOW NOISE AMPLIFIER APPLICATIONS

Unit in mm


- TWO devices are built in to the super-thin and ultra super mini (6 pins) package : TU6

MOUNTED DEVICES


| | |
|--|----------------------|
| | Q1 / Q2 : SSM (TESM) |
| Three-pins (SSM/ TESM) mold products are corresponded. | MT3S04AS (MT3S04AT) |

MAXIMUM RATINGS (Ta = 25°C)


| CHARACTERISTIC | SYMBOL | Q1 / Q2 | UNIT |
|-----------------------------|------------------|---------|------|
| Collector-Base Voltage | V _{CB0} | 10 | V |
| Collector-Emitter Voltage | V _{CEO} | 5 | V |
| Emitter-Base Voltage | V _{EB0} | 2 | V |
| Collector Current | I _C | 40 | mA |
| Base Current | I _B | 10 | mA |
| Collector Power Dissipation | P _C | 200 | mW |
| Junction Temperature | T _j | 125 | °C |
| Storage Temperature Range | T _{stg} | -55~125 | °C |



MARKING



PIN ASSIGNMENT (TOP VIEW)



961001EAA1

- TOSHIBA is continually working to improve the quality and the reliability of its products. Nevertheless, semiconductor devices in general can malfunction or fail due to their inherent electrical sensitivity and vulnerability to physical stress. It is the responsibility of the buyer, when utilizing TOSHIBA products, to observe standards of safety, and to avoid situations in which a malfunction or failure of a TOSHIBA product could cause loss of human life, bodily injury or damage to property. In developing your designs, please ensure that TOSHIBA products are used within specified operating ranges as set forth in the most recent products specifications. Also, please keep in mind the precautions and conditions set forth in the TOSHIBA Semiconductor Reliability Handbook.
- The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by TOSHIBA CORPORATION for any infringements of intellectual property or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any intellectual property or other rights of TOSHIBA CORPORATION or others.
- The information contained herein is subject to change without notice.

ELECTRICAL CHARACTERISTICS Q1/Q2 (Ta = 25°C)

| CHARACTERISTIC | SYMBOL | TEST CONDITION | MIN. | TYP. | MAX. | UNIT |
|------------------------------|------------------|--|------|------|------|---------------|
| Collector Cut-off Current | I_{CBO} | $V_{CB} = 5\text{ V}, I_E = 0$ | — | — | 0.1 | μA |
| Emitter Cut-off Current | I_{EBO} | $V_{EB} = 1\text{ V}, I_C = 0$ | — | — | 1 | μA |
| DC Current Gain | h_{FE} | $V_{CE} = 1\text{ V}, I_C = 5\text{ mA}$ | 80 | — | 160 | — |
| Transition Frequency | $f_T(1)$ | $V_{CE} = 1\text{ V}, I_C = 5\text{ mA}$ | 2 | 4.5 | — | GHz |
| | $f_T(2)$ | $V_{CE} = 3\text{ V}, I_C = 7\text{ mA}$ | 5 | 7 | — | GHz |
| Insertion Gain | $ S_{21e} ^2(1)$ | $V_{CE} = 1\text{ V}, I_C = 5\text{ mA},$ $f = 1\text{ GHz}$ | — | 8.5 | — | dB |
| | $ S_{21e} ^2(2)$ | $V_{CE} = 3\text{ V}, I_C = 20\text{ mA},$ $f = 1\text{ GHz}$ | 7.5 | 11 | — | dB |
| Noise Figure | NF (1) | $V_{CE} = 1\text{ V}, I_C = 5\text{ mA},$ $f = 1\text{ GHz}$ | — | 1.3 | 2.2 | dB |
| | NF (2) | $V_{CE} = 3\text{ V}, I_C = 7\text{ mA},$ $f = 1\text{ GHz}$ | — | 1.2 | 2 | dB |
| Reverse Transfer Capacitance | C_{re} | $V_{CB} = 1\text{ V}, I_E = 0,$ $f = 1\text{ MHz (Note)}$ | — | 0.9 | 1.25 | pF |

(Note) : C_{re} is measured by 3 terminal method with capacitance bridge.

HANDLING PRECAUTION

When handling individual devices (which are not yet mounting on a circuit board), be sure that the environment is protected against electrostatic electricity. Operators should wear anti-static clothing, and containers and other objects that come into direct contact with devices should be made of anti-static materials.