

Low Noise Amplifier, 12 dB Gain, 300 - 1800 MHz

Rev. V3

#### **Features**

- 1.9 dB Typical Midband Noise Figure
- +7.5 dBm Typical Midband Output Power
- +19 dBm Typical Midband Third Order Intercept

### **Description**


M/A-COM's AM-153 is a coupler feedback amplifier with low noise figure. The use of coupler feedback minimizes noise figure and current in a high intercept amplifier. This amplifier is packaged in a TO-8 package. This unique design features low noise figure over a wide bandwidth. AM-153 is ideally suited for use where a low noise, wideband, high reliability amplifier is required.

# Absolute Maximum Ratings 1

Parameter	Absolute Maximum		
Max. Input Power	+10 dBm		
Vbias	+15.75 V		
Operating Temperature	-55°C to +85°C		
Storage Temperature	-65°C to +125°C		

<sup>1.</sup> Operation of this device above any one of these parameters may cause permanent damage.

#### TO-8-1



Diversions in O are in no Unless Otherwise Hotself (XXX = ±0,000 CXX = ±0,25) XX = 40,00 CX = 40,00 VEX.HT (APPROID) (30 CUNCES = 20 GAMS

Electrical Specifications: <sup>2</sup> T<sub>A</sub> = -55°C to +85°C Case Temperature

Parameter	Test Conditions	Frequency	Units	Min.	Тур.	Max.
Gain	@+25°C	600 MHz	dB	11.9	12.4	12.9
Frequency Response	_	300 - 1800 MHz	dB	_	_	±1.2
Gain Variation with Temperature	_	300 - 1800 MHz	dB	_	_	+0.5, -0.7
1 dB Compression	Output Power	300 - 1800 MHz	dBm	+6	_	_
Noise Figure	_	300 - 1800 MHz 1500 - 1800 MHz	dB dB	_	_	3.0 3.5
Reverse Transmission	_	300 - 1800 MHz	dB	_	-14	-12
VSWR Input	_	300 - 1800 MHz 1500 - 1800 MHz	Ratio Ratio		_	2.5:1 3.3:1
VSWR Output	_	300 - 400 MHz 400 - 1500 MHz 1500 - 1800 MHz	Ratio Ratio Ratio			3.5:1 3.0:1 2.5:1
Output IP <sub>2</sub>	Two-Tone inputs up to -5 dBm	300 - 1800 MHz	dBm	+22	_	_
Output IP <sub>3</sub>	Two-Tone inputs up to -5 dBm	300 - 1000 MHz 1000 - 1800 MHz	dBm dBm	+17 +15		
Vbias	_	_	VDC	+14.5	+15.0	+15.5
Ibias	Vbias = +15.0 VDC	_	mA	_	13	15
Power Dissipation	@ +15 V Bias	_	mW	_	200	_

<sup>2.</sup> All specifications apply when operated at +15 VDC, with 50 ohms source and load impedance.

- North America Tel: 800.366.2266 Europe Tel: +353.21.244.6400
- India Tel: +91.80.4155721 China Tel: +86.21.2407.1588

  Visit www.macomtech.com for additional data sheets and product information.




Low Noise Amplifier, 12 dB Gain, 300 - 1800 MHz


Rev. V3

## **Typical Performance Curves**


#### Gain vs. Frequency




#### Noise Figure




#### Intermodulation Intercept



#### VSWR vs. Frequency



### 1 dB Compression



## **Ordering Information**

Part Number	Package
AM-153 PIN <sup>3</sup>	TO-8-1

3. Mounting kit part number AU00071 required for PCB applications.

Commitment to produce in volume is not guaranteed.

• North America Tel: 800.366.2266 • Europe Tel: +353.21.244.6400

• India Tel: +91.80.4155721 Visit www.macomtech.com for additional data sheets and product information.

• China Tel: +86.21.2407.1588