

## Power Transformer Chassis Mount: Quick Pack

# **F4-36**

### **Description:**

The F4-36 Quick Pack small power transformer offers a significant reduction in size and weight over a standard transformer. This transformer can be used for a wide variety of applications. It is bobbin wound for reduced size and small operating space.

#### Electrical Specifications (@25C);

Maximum Power: 6.0VA Input Voltage: 115VAC@50/60Hz Output Voltage: 36VCT@0.17A Hipot: 2500VAC primary to secondary; 1500VAC windings to core.

#### **Construction:**

Split bobbin non concentric winding eliminates costly electrostatic shielding. Termination is suitable for quick connects or soldering. Built with UL Class B Insulation System.

#### Safety:

UL: File E53148, UL 5085-1 and 2 (formerly UL 506), General Purpose.




#### **Dimensions:**

| А     | В       | С     | D     | Е     | F        | G    |
|-------|---------|-------|-------|-------|----------|------|
| 1.375 | 2.0±.03 | 2.375 | 1.250 | 1.687 | .187 Dia | .687 |

Notes: 1. Units: inches.

- 2. Terminal size: .187" X 0.021".
- 3. Weight: .44 lbs

#### Schematic:



**Input:** Input 2 & 3 **Output:** 5 to 8


**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

\* Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics' website for the most current version.

| Web: www.TriadMagnetics.com |
|-----------------------------|
| Phone 951-277-0757          |
| Fax 951-277-2757            |

460 Harley Knox Blvd. Perris, California 92571





Publish Date: December 4, 2013