
DISCRETE SEMICONDUCTORS

DATA SHEET



BGE887BOOptical receiver module

Product specification Supersedes data of 2000 Apr 10 2001 Sep 27





Optical receiver module

BGE887BO

FEATURES

- · Excellent linearity
- · Extremely low noise
- · Excellent flatness
- · Standard CATV outline
- Rugged construction
- · Gold metallization ensures excellent reliability.

APPLICATIONS


 CATV systems operating in the 40 to 860 MHz frequency range.

DESCRIPTION

Hybrid high dynamic range optical receiver module in a SOT115U package operating at a voltage supply of +24 V (DC). The module contains a monomode optical input suitable for wavelengths from 1290 to 1600 nm, a terminal to monitor the pin diode current and an electrical output with an impedance of 75 Ω .

PINNING - SOT115U

PIN	DESCRIPTION	
1	monitor current	
2	common	
3	common	
5	+V _B	
7	common	
8	common	
9	output	



QUICK REFERENCE DATA

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.	UNIT
f	frequency range		40	860	MHz
S ₂₂	output return losses	f = 40 to 860 MHz	11	_	dB
	optical input return losses		45	_	dB
d_2	second order distortion	f = 324.25 MHz	_	-70	dBc
F	equivalent noise input	f = 40 MHz	_	7	pA/√Hz
I _{tot}	total current consumption (DC)	V _B = 24 V	175	205	mA

HANDLING

Fibreglass optical coupling: maximum tensile strength = 5 N; minimum bending radius = 35 mm.

Philips Semiconductors Product specification

Optical receiver module

BGE887BO

LIMITING VALUES

In accordance with the Absolute Maximum Rating System (IEC 60134).

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.	UNIT
f	frequency range		40	860	MHz
T _{stg}	storage temperature		-40	+85	°C
T _{mb}	operating mounting base temperature		-20	+85	°C
P _{in}	optical input power	continuous	_	5	mW
ESD	ESD sensitivity	human body model; R = 1.5 kΩ; C = 100 pF	500	_	V

CHARACTERISTICS

Table 1 Bandwidth 40 to 860 MHz; $V_B = 24 \text{ V}$; $T_{mb} = 30 \,^{\circ}\text{C}$; $Z_S = Z_L = 75 \,^{\circ}\Omega$

SYMBOL	PARAMETER	CONDITIONS	MIN.	MAX.	UNIT
S	responsivity	λ = 1300 nm	800	_	V/W
V _{pin 1}	pin 1 monitor voltage	λ = 1300 nm	0.75	1	V/mW
FL	flatness of frequency response – ±0		±0.5	dB	
S ₂₂	output return losses	f = 40 to 860 MHz	11	_	dB
	optical input return losses		45	_	dB
d ₂	second order distortion	note 1	_	-70	dB
d ₃	third order distortion	note 2	_	-80	dB
F	equivalent noise input	f = 40 MHz	_	7	pA/√Hz
s_λ	spectral sensitivity	$\lambda = 1310 \pm 20 \text{ nm}$	0.85	_	A/W
		$\lambda = 1550 \pm 20 \text{ nm}$	0.9	_	A/W
λ	optical wavelength		1290	1600	nm
L	length of optical fibre	fibre; SM type; 9/125 μm	1	-	m
I _{tot}	total current consumption (DC)	note 3	175	205	mA

Notes

Two laser test; each laser with 40% modulation index;
 f_p = 135 MHz; P_p = 0.5 mW;

$$\begin{split} f_q &= 189.25 \text{ MHz}; \ P_q = 0.5 \text{ mW}; \\ \text{measured at } f_p + f_q &= 324.25 \text{ MHz}. \end{split}$$

2. Three laser test; each laser with 40% modulation index;


 $f_p = 326.25 \text{ MHz}; P_p = 0.33 \text{ mW};$

 $f_q = 333.25 \text{ MHz}; P_q = 0.33 \text{ mW};$

 $f_r = 335.25 \text{ MHz}; P_r = 0.33 \text{ mW};$

measured at $f_p + f_q - f_r = 324.25$ MHz.

3. The module normally operates at $V_B = 24 \text{ V}$ but is able to withstand supply transients up to 30 V.



2001 Sep 27

Philips Semiconductors Product specification


Optical receiver module

BGE887BO

PACKAGE OUTLINE

Rectangular single-ended package; aluminium flange; 2 vertical mounting holes; 2 x 6-32 UNC and 2 extra horizontal mounting holes; optical input; 7 gold-plated in-line leads

SOT115U



Philips Semiconductors Product specification

Optical receiver module

BGE887BO

DATA SHEET STATUS

DATA SHEET STATUS(1)	PRODUCT STATUS ⁽²⁾	DEFINITIONS
Objective data	Development	This data sheet contains data from the objective specification for product development. Philips Semiconductors reserves the right to change the specification in any manner without notice.
Preliminary data	Qualification	This data sheet contains data from the preliminary specification. Supplementary data will be published at a later date. Philips Semiconductors reserves the right to change the specification without notice, in order to improve the design and supply the best possible product.
Product data	Production	This data sheet contains data from the product specification. Philips Semiconductors reserves the right to make changes at any time in order to improve the design, manufacturing and supply. Changes will be communicated according to the Customer Product/Process Change Notification (CPCN) procedure SNW-SQ-650A.

Notes

- 1. Please consult the most recently issued data sheet before initiating or completing a design.
- 2. The product status of the device(s) described in this data sheet may have changed since this data sheet was published. The latest information is available on the Internet at URL http://www.semiconductors.philips.com.

DEFINITIONS

Short-form specification — The data in a short-form specification is extracted from a full data sheet with the same type number and title. For detailed information see the relevant data sheet or data handbook.

Limiting values definition — Limiting values given are in accordance with the Absolute Maximum Rating System (IEC 60134). Stress above one or more of the limiting values may cause permanent damage to the device. These are stress ratings only and operation of the device at these or at any other conditions above those given in the Characteristics sections of the specification is not implied. Exposure to limiting values for extended periods may affect device reliability.

Application information — Applications that are described herein for any of these products are for illustrative purposes only. Philips Semiconductors make no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

DISCLAIMERS

Life support applications — These products are not designed for use in life support appliances, devices, or systems where malfunction of these products can reasonably be expected to result in personal injury. Philips Semiconductors customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify Philips Semiconductors for any damages resulting from such application.

Right to make changes — Philips Semiconductors reserves the right to make changes, without notice, in the products, including circuits, standard cells, and/or software, described or contained herein in order to improve design and/or performance. Philips Semiconductors assumes no responsibility or liability for the use of any of these products, conveys no licence or title under any patent, copyright, or mask work right to these products, and makes no representations or warranties that these products are free from patent, copyright, or mask work right infringement, unless otherwise specified.

CAUTION

This product is supplied in anti-static packing to prevent damage caused by electrostatic discharge during transport and handling. For further information, refer to Philips specs.: SNW-EQ-608, SNW-FQ-302A and SNW-FQ-302B.

Optical receiver module

BGE887BO

NOTES

Optical receiver module

BGE887BO

NOTES

Philips Semiconductors – a worldwide company

Contact information

For additional information please visit http://www.semiconductors.philips.com. Fax: +31 40 27 24825 For sales offices addresses send e-mail to: sales.addresses@www.semiconductors.philips.com.

© Koninklijke Philips Electronics N.V. 2001

SCA73

All rights are reserved. Reproduction in whole or in part is prohibited without the prior written consent of the copyright owner.

The information presented in this document does not form part of any quotation or contract, is believed to be accurate and reliable and may be changed without notice. No liability will be accepted by the publisher for any consequence of its use. Publication thereof does not convey nor imply any license under patent- or other industrial or intellectual property rights.

Printed in The Netherlands

613518/05/pp8

Date of release: 2001 Sep 27

Document order number: 9397 750 08694

Let's make things better.





