






Triacs

(Continued)

I_T (AMPS)	30	35	40		45
@ T_C (°C)	90	90	90	90	90
I_{TSM} (AMPS)	250	300	300	300	300
CASE					
	TO-218	TO-48	TO-3P ISOLATED	TO-218 ISOL ISOLATED	TO-218
V_{RRM} (VOLTS)					
200	CQ218-30B*	CQ48-35B*	CQ3P-40B	CQ218I-40B	CQ218-45B
400	CQ218-30D*	CQ48-35D*	CQ3P-40D	CQ218I-40D	CQ218-45D
600	CQ218-30M*	CQ48-35M*	CQ3P-40M	CQ218I-40M	CQ218-45M
800	CQ218-30N*	CQ48-35N*	CQ3P-40N	CQ218I-40N	CQ218-45N

$I_{GT\ QI}$	50mA	100mA	50mA	50mA	50mA
$I_{GT\ QII}$	50mA	100mA	50mA	50mA	50mA
$I_{GT\ QIII}$	50mA	100mA	50mA	50mA	50mA
$I_{GT\ QIV}$	100mA	150mA	100mA	100mA	100mA
$V_{GT\ QI-QIV}$	1.5V	1.5V	1.5V	1.5V	1.5V
I_H	80mA	100mA	80mA	80mA	80mA

* Not recommended for new designs.

Central[™]
Semiconductor Corp.
www.centrasemi.com

www.DataSheet4U.com