




MECHANICAL DATA

Dimensions in mm (inches)



TO-39 (TO205AD)

Underside View

PIN 1 - Emitter PIN 2 - Base PIN 3 - Collector

PNP SILICON TRANSISTOR

FEATURES

- High Voltage
- Hermetic TO39 Package
- Full Screening Options Available

ABSOLUTE MAXIMUM RATINGS (T_{case} = 25°C unless otherwise stated)

| V_{CBO} | Collector – Base Voltage (I _E = 0) | -300V |
|-----------------|--|--------------|
| V_{CEO} | Collector – Emitter Voltage (I _B = 0) | -300V |
| V_{EBO} | Emitter – Base Voltage (I _B = 0) | -5V |
| I _C | Collector Current | -0.5A |
| P_{D} | Total Device Dissipation $T_C = 50^{\circ}C$ | 5W |
| T_{stg} | Storage Temperature | −65 to 150°C |
| T_J | Junction Temperature | 200°C |
| $R_{	heta JA}$ | Thermal Resistance Junction to Ambient | 200°C/W |
| $R_{\theta JC}$ | Thermal Resistance Junction to Case | 30°C/W |

Semelab PIc reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by Semelab is believed to be both accurate and reliable at the time of going to press. However Semelab assumes no responsibility for any errors or omissions discovered in its use. Semelab encourages customers to verify that datasheets are current before placing orders.

Semelab plc. Telephone +44(0)1455 556565. Fax +44(0)1455 552612. E-mail: sales@semelab.co.uk

Website: http://www.semelab.co.uk





ELECTRICAL CHARACTERISTICS (T_{case} = 25°C unless otherwise stated)

| | Parameter | Test Conditions | | Min | Тур | Max | Unit |
|-----------------------|--|-------------------------|-------------------------|------|-----|------|------|
| V _{(BR)CEO} | Collector – Emitter Breakdown Voltage | $I_C = -10mA$, | I _B = 0 | -300 | | | V |
| I _{CBO} | Collector Cut-off Current | V _{CB} = -200V | I _E = 0 | | | -5 | μΑ |
| I _{EBO} | Emitter Cut-off Current | V _{BE} = -3V | I _C = 0 | | | -5 | μΑ |
| V _{CE(sat)*} | Collector – Emitter Saturation Voltage | I _C =-10mA, | I _B =-1.0mA | | | -0.5 | |
| | | I _C =-100mA, | I _B =-10mA | | | -1.4 | V |
| | | I _C =-500mA, | I _B =-100mA | | | -5.0 | |
| V _{BE(sat)*} | Base – Emitter Saturation Voltage | I _C =-10mA, | I _B =-1.0mA | | | -0.8 | V |
| | | I _C =-100mA, | I _B =-10mA | | | -0.9 | |
| | | I _C =-500mA, | I _B =-100mA | | | -1.2 | |
| h _{FE*} | DC Current Gain | V _{CE} = -10V | $I_C = -1.0 \text{mA}$ | 30 | | | |
| | | V _{CE} = -10V | I _C = -10mA | 50 | | 150 |] - |
| | | V _{CE} = -10V | I _C = -100mA | 50 | | | |

DYNAMIC CHARACTERISTICS (T_{case} = 25°C unless otherwise stated)

| Parameter | | Test Conditions | Min. | Тур. | Max. | Unit |
|------------------|-----------------------|---|------|------|------|------|
| f _T | Transition Frequency | $I_{C} = -15 \text{mA}$ $V_{CE} = -10 \text{V}$ $f = 35 \text{MHz}$ | | 70 | | MHz |
| C _c | Collector Capacitance | $V_{CB} = -20V$ $I_E = 0$ $f = 1MHz$ | | | 15 | pF |
| t _{on} | Lurn on Lime | V_{CC} =-31V , I_{C} =-50mA, I_{B1} = I_{B2} =5mA | | 125 | | ns |
| | | V_{CC} =-31V , I_{C} =-500mA, I_{B1} = I_{B2} =100mA | | 125 | | ns |
| t _{off} | Lurn off Lime | V_{CC} =-31V , I_{C} =-50mA, I_{B1} = I_{B2} =5mA | | 850 | | ns |
| | | V_{CC} =-31V , I_{C} =-500mA, I_{B1} = I_{B2} =100mA | | 125 | | ns |

(*) Pulse test : Pulse Width $< 300 \mu s$, Duty Cycle < 2%

Semelab PIc reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by Semelab is believed to be both accurate and reliable at the time of going to press. However Semelab assumes no responsibility for any errors or omissions discovered in its use. Semelab encourages customers to verify that datasheets are current before placing orders.

E-mail: sales@semelab.co.uk

Semelab plc. Telephone +44(0)1455 556565. Fax +44(0)1455 552612. Website: http://www.semelab.co.uk