

# PI3V512

### Low On-Resistance, 3.3V Wideband/Video Switch 5-Port, 2:1 Mux/DeMux


#### Features

- → RON is 4Ω typical
- → Low bit-to-bit skew: 200ps
- → Low crosstalk: -65dB @ 10MHz
- → Low Current Consumption: 20µA
- ➔ Near-Zero propagation delay: 250ps
- → Switching speed: 9ns
- → Channel On-Capacitance: 6pF (typical)
- → VDD Operating Range: +3.0V to +3.6V
- → ESD>2000V . . . Human Body Model
- → High Signal Passing bandwidth (600 MHz)
- ➔ Packaging (Pb-free & Green available): -24-pin QSOP (Q)

#### **Applications**

- → Projection TV and LCD TV
- → Video consumer applications
- ➔ Analog video signal processing

#### **Block Diagram**



#### Description

Pericom Semiconductor's PI3V512 is a true bi-directional 5-Port 2:1 multiplexer/demultiplexer with Hi-Z outputs that is recommended for both RGB and composite video switching applications. With the additional 2 ports, vertical and horizontal synchronous signals can be switched in addition to switching the RGB and composite signals between different components, such as DVD, VCR, PCs and etc. The VideoSwitch can be driven from a current output RAMDAC or voltage output composite video source.

Low On-Resistance, Low Crosstalk, Low OFF Isolation and wide bandwidth features make it ideal for video and other applications. Industry leading advantages include a propagation delay of less than 250ps, resulting from its low channel resistance and I/O capacitance. The switch is bi-directional and offers little or no attenuation of the high-speed signals at the outputs. The device also has exceptional high current capability which is far greater than most analog switches offered today. The PI3V512 offers a high-performance (600 MHz), low-cost solution to switch between video sources.

#### **Pin Description**

V <sub>DD</sub>		24	IA0
Y <sub>A</sub>	2		IA1
GND	3		IB0
V <sub>DD</sub>	4		IB1
Y <sub>B</sub>	5	20	GND
Yc 🗌	6	19	Vdd
GND	7		IC0
Y <sub>D</sub>	8	17	ID0
Vdd [	9		IC1
GND	10	15	ID1
Ye 🗌	11	14	IE0
SEL	12	13	IE1
7			

#### **Maximum Ratings**

(Above which useful life may be impaired. For user guidelines, not tested.)

Storage Temperature	65°C to +150°C
Supply Voltage to Ground Potential	0.5V to +4.0V
DC Input Voltage	0.5V to +5.5V
DC Output Current	120mA
Power Dissipation	0.5W
1	

#### Note:

Stresses greater than those listed under MAXIMUM RATINGS may cause permanent damage to the device. This is a stress rating only and functional operation of the device at these or any other conditions above those indicated in the operational sections of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect reliability.

#### **Truth Table**

Function	SEL
Y <sub>N</sub> to IN0	L
Y <sub>N</sub> to IN1	Н

Paramenter	Description	Test Conditions	Min.	Typ. <sup>(2)</sup>	Max.	Units
V <sub>IH</sub>	Input HIGH Voltage	Guaranteed HIGH level	2	-	-	
V <sub>IL</sub>	Input LOW Voltage	Guaranteed LOW level	-0.5	-	0.8	V
V <sub>IK</sub>	Clamp Diode Voltage	$V_{DD} = Max., I_{IN} = -18mA$	-	-0.7	-1.2	
I <sub>IH</sub>	Input HIGH Current	$V_{DD} = Max., V_{IN} = V_{DD}$	-	-	±5	
I <sub>IL</sub>	Input LOW Current	V <sub>DD</sub> = Max., V <sub>IN</sub> = GND	-	-	±5	μA
I <sub>OFF</sub>	Power Down Leakage Current	$V_{DD} = 0V, V_A = 0V, V_B \le 3.6$	-	-	10	
R <sub>ON</sub>	Switch On-Resistance <sup>(3)</sup>	$V_{DD} = Min., 1.5V \le V_{IN} \le V_{DD},$ $I_{IN} = -40mA$	-	4	8	
R <sub>FLAT(ON)</sub>	On-Resistance Flatness <sup>(4)</sup>	$V_{DD}$ = Min., $V_{IN}$ @ 1.5V and $V_{DD}$ , $I_{IN}$ = -40mA	-	1	-	Ω
ΔR <sub>ON</sub>	On-Resistance match from center ports to any other port <sup>(4)</sup>	$V_{DD} = Min., 1.5V \le V_{IN} \le V_{DD},$ $I_{IN} = -40mA$	-	0.9	2	

#### DC Electrical Characteristics ( $T_A = -40^{\circ}C$ to $+85^{\circ}C$ , $V_{DD} = 3.3V \pm 10\%$ )

Paramenter	Description	Test Conditions	Min.	Typ. <sup>(2)</sup>	Max.	Units
V <sub>IH</sub>	Input HIGH Voltage	Guaranteed HIGH level	2.0	-	-	
V <sub>IL</sub>	Input LOW Voltage	Guaranteed LOW level	-0.5	-	0.8	V
V <sub>IK</sub>	Clamp Diode Voltage	$V_{DD} = Max., I_{IN} = -18mA$	-	-0.7	-1.2	
I <sub>IH</sub>	Input HIGH Current	$V_{DD} = Max., V_{IN} = V_{DD}$	-	-	±5	
I <sub>IL</sub>	Input LOW Current	V <sub>DD</sub> = Max., V <sub>IN</sub> = GND	-	-	±5	μA
I <sub>OFF</sub>	Power Down Leakage Current	$V_{DD} = 0V, V_A = 0V, V_B \le 3.6$	-	-	-	
R <sub>ON</sub>	Switch On-Resistance <sup>(3)</sup>	$\label{eq:VDD} \begin{array}{l} V_{DD} = Min., \ 1.25V \leq V_{IN} \leq \ V_{DD}, \\ I_{IN} = -10mA \ to \ -30mA \end{array}$	-	-	8	
R <sub>FLAT(ON)</sub>	On-Resistance Flatness <sup>(4)</sup>	$V_{DD}$ = Min., $V_{IN}$ @ 1.25V and $V_{DD,}$ $I_{IN}$ = –10mA to –30mA	-	1.0	-	Ω
$\Delta R_{ON}$	On-Resistance match from center ports to any other port <sup>(4)</sup>	$\label{eq:VDD} \begin{array}{l} V_{DD} = Min., \ 1.25V \leq V_{IN} \leq V_{DD}, \\ I_{IN} = -10mA \ to \ -30mA \end{array}$	-	0.9	2.0	

#### **DC Electrical Characteristics** ( $T_A = -40^{\circ}C$ to $+85^{\circ}C$ , $V_{DD} = 3.3V \pm 10\%$ )

#### Capacitance $(T_A = 25^{\circ}C, f = 1MHz)$

Parameters <sup>(5)</sup>	Description	Test Conditions	Тур.	Max.	Units
C <sub>IN</sub>	Input Capacitance		2.0	3.0	
C <sub>OFF</sub> (IN0, IN1)	Port I Capacitance, Switch OFF	$V_{IN} = 0V$	4.0	6.0	pF
C <sub>ON(Y/I)</sub>	Y/I Capacitance, Switch ON		6.0	10.0	

Notes:

1. For max. or min. conditions, use appropriate value specified under Electrical Characteristics for the applicable device type.

2. Typical values are at  $V_{DD}$  = 3.3V,  $T_A$  = 25°C ambient and maximum loading.

3. Measured by the voltage drop between Y and I pins at indicated current through the switch. On-Resistance is determined by the lower of the voltages on the two (Y & I) pins.

4. This parameter is determined by device characterization but is not production tested.

#### **Power Supply Characteristics**

Parameters	Description	Test Conditions <sup>(1)</sup>	Min.	Typ. <sup>(2)</sup>	Max.	Units
I <sub>CC</sub>	Quiescent Power Supply Current	$V_{DD}$ = Max., $V_{IN}$ = GND or $V_{DD}$	-	-	800	μA

Notes:

1. For max. or min. conditions, use appropriate value specified under Electrical Characteristics for the applicable device type.

2. Typical values are at  $V_{DD}$  = 3.3V,  $T_A$  = 25°C ambient and maximum loading.

3. Per TTL driven input (control inputs only); Y and I pins do not contribute to  $I_{\rm CC}.$ 

### Dynamic Electrical Characteristics Over the Operating Range ( $T_A$ =-40° to +85°C,

V<sub>CC</sub>=3.3V±10%, GND=0V)

Parameter	Description	Test Conditions	Min.	Typ. <sup>(2)</sup>	Max.	Units
X <sub>TALK</sub>	Crosstalk	See Test Diagram (f = 10 MHz)	-	-65	-	dB
O <sub>IRR</sub>	OFF Isolation	See Test Diagram $(I = 10 \text{ MHz})$	-	-70	-	ub
BW	Bandwidth –3dB	See Test Diagram ( $C_L = 0 \text{ pF}$ )	-	600	-	MHz

#### **Switching Characteristics**


Paramenter	Description	Min.	Typ. <sup>(2)</sup>	Max.	Units
t <sub>PD</sub>	Propagation Delay <sup>(2,3)</sup>	-	0.25		
t <sub>PZH</sub> , t <sub>PZL</sub>	Line Enable Time - SEL to $Y_N$ , $I_N$	0.5	-	15	
t <sub>PHZ</sub> , t <sub>PLZ</sub>	Line Disable Time - SEL to $Y_N$ , $I_N$	0.5	-	9	ns
t <sub>SK(o)</sub>	Output Skew between center port (YC to YD) to any other port <sup>(2)</sup>	-	0.1	0.2	
t <sub>SK(p)</sub>	Skew between opposite transitions of the same output $(t_{PHL} - t_{PLH})^{(2)}$	-	0.1	0.2	

Notes:

1. For max. or min. conditions, use appropriate value specified under Electrical Characteristics for the applicable device type.


2. Guaranteed by design.

3. The bus switch contributes no propagational delay other than the RC delay of the On-Resistance of the switch and the load capacitance. The time constant for the switch alone is of the order of 0.25ns for 10pF load. Since this time constant is much smaller than the rise/fall times of typical driving signals, it adds very little propagational delay to the system. Propagational delay of the bus switch when used in a system is determined by the driving circuit on the driving side of the switch and its interactions with the load on the driven side.



### **Bandwidth vs. Capacitance**

### Test Circuit for Electrical Characteristics<sup>(1)</sup>




#### Notes:

- 1.  $C_L$  = Load capacitance: includes jig and probe capacitance.
- 2.  $R_T$  = Termination resistance: should be equal to  $Z_{OUT}$  of the Pulse Generator
- 3. Waveform 1 is for an output with internal conditions such that the output is low except when disabled by the output control. Waveform 2 is for an output with internal conditions such that the output is high except when disabled by the output control.
- 4. All input impulses are supplied by generators having the following characteristics: PRR  $\leq$  MHz,  $Z_O = 50\Omega$ ,  $t_R \leq 2.5$ ns,  $t_F \leq 2.5$ ns.
- 5. The outputs are measured one at a time with one transition per measurement.

#### **Switch Positions**


Test	Switch
t <sub>PLZ</sub> , t <sub>PZL</sub> (output on I side)	6.0V
t <sub>PHZ</sub> , t <sub>PZH</sub> (output on I side)	GND
Prop Delay	Open

#### **Test Circuit for Dynamic Electrical Characteristics**







## Off Isolation ( $V_{DD}$ 3.3V, 25°C)



## Crosstalk (V<sub>DD</sub> 3.3V, 25°C)



#### **Switching Waveforms**




## **Applications Information**

### Logic Inputs

The logic control inputs can be driven up to +3.6V regardless of the supply voltage. For example, given a +3.3V supply, the output enables or select pins may be driven low to 0V and high to 3.6V. Driving IN Rail-to-Rail<sup>®</sup> minimizes power consumption.

Rail-to-Rail is a registered trademark of Nippon Motorola, Ltd

### Packaging Mechanical: 24-pin QSOP (Q)



)7-0475

#### **Ordering Information**

Ordering Code	Package Code	Package Description
PI3V512QE	Q	Pb-free & Green, 24-pin 150 mil wide plastic QSOP

#### Notes:

1. Thermal characteristics can be found on the company web site at www.pericom.com/packaging/

Pericom Semiconductor Corporation • 1-800-435-2336 • www.pericom.com