



FCS-3101 Version: 1

2-Megapixel Day/Night PoE Mini Dome Network Camera - IR LEDs

The LevelOne FCS-3101 is a palm-size and stylish design quality yet cost-effective surveillance solution for the home and office. It is designed for easy and flexible installation. Equipped with a 2-Megapixel sensor and built-in IR cut filter/IR illuminator LEDs, the camera provides high resolution quality and sharp sensitivity – ideal for security applications both day and night.

The FCS-3101 is equipped with many advanced features such as Level1DNS™ Service, alarm and sensor, a micro SD/SDHC card slot and USB interface for local storage, built-in microphone communications. Moreover, Support unique features for auto tracking function of moving objects, the system can send an E-mail alert or send captured images via FTP upload to a designated storage server. The FCS-3101 is indisputably the top choice for reliable and high performance surveillance.



5 1 6 7 8

- 1. Housing Latch
- 2. Power Socket
- 3. PoE LAN Port
- 4. Lens

- 5. IR LED
- 6. Internal Microphone
- 7. Micro SD/SDHC Card slot
- 8. Reset Button

Key Features

- 2-Megapixel (1920 x 1080) high-definition resolution
- Compression: H.264/MPEG-4/MJPEG
- Removable IR-cut filter for day and night surveillance
- Supports 2 video streams simultaneously
- Built-in infrared LEDs for night viewing up to 10m

www.level1.com Page 1 of 5

- Built-in Micro SD/SDHC card slot for local storage
- Built-in microphone for audio monitoring
- Dual power support: 12VDC/PoE (IEEE 802.3af)
- Free 64-channel monitoring software included (supports iCamSecure App)

Specifications

System Specifications

Image Sensor:

2-Megapixel 1/2.7" Progressive Scan CMOS

Connectors and Cabling:

1 x RJ-45 10/100 Mbps PoE port

1 x DC Power Jack

1 x Built-in microphone

Modularity:

1 x MicroSD/SDHC card slot

Button:

Reset Button

Indicator:

Power, Link

Lens:

Board lens, fixed-focal, f=4.0 mm, F2.0

IR Cut Filter:

Removable infrared-cut filter for day & night function

IR LED:

19 IR LEDs for illumination up to 10m

Shutter Time:

Indoor: 1/30 ~ 1/120 sec

Outdoor: 1/30 ~ 1/1,000,000 sec

Angle of View:

62°

Video Compression:

H.264 / MPEG4 / MJPEG

Resolution:

1080p (1920x1080) / SXGA (1280x1024) / WXGA (1280x800) / VGA (640x480) / QVGA (320x240) / QCIF (176x144)

Video Format:

AVI

Audio Compression:

AMR / AAC

Power:

Power Consumption: 6W

Power Input: DC12V 1.5A / AC24V / 802.3af PoE

Standards & Protocols:

IEEE 802.3 10-BASE-T, Ethernet

IEEE 802.3u 100-BASE-TX, Fast Ethernet

TCP/IP, HTTP, SMTP, FTP, DDNS, UPnP, Telnet, NTP, PPPoE, DNS, DHCP, RTSP, Samba

Features

www.level1.com Page 2 of 5

General:

Backup: MicroSD/SDHC card slot for local storage

IPv6: IPv4/IPv6 network operationDNS: Easy Internet monitoring via configuration free Level1DNS™ service

Security:

Alarm and Notification: Alarm: Motion Detection; Notification: FTP, SMTP, Samba

Access Control: Multi-level user access with password protection

IP address filtering

HTTPS encrypted data transmission

Video:

Image Setting: - Adjustable image size, quality and bit rate

- Configurable brightness, sharpness, contrast, saturation, white balance and exposure
- AGC/AWB/AEC
- Wide Dynamic Range (WDR)
- Flip & Mirror
- Time Stamp

Streaming: Up to 2 video streams

Audio:

Streaming: 1-way audio

Input/Output: Built-in microphone

Performance

Number of Clients:

16

Data Transfer Rate:

10/100Mbps

Frame Rate:

Up to 30 fps at 1920x1080

Minimum illumination:

Color: 1.0 lux at F2.0 B/W: 1.0 lux at F2.0

Environment

Temperature (°C):

Operating: 0°C ~ 40°C

Humidity (Non-condensing):

Operating: 10% ~ 80%

Physical Specifications

Dimensions (W x D x H mm):

63 x 63 x 92 mm

Weight (g):

380g

Others

Approval and Compliance:

CE, FCC

Deployment:

Desktop/Ceiling Mount

Operation Systems:

Microsoft Windows 7/Vista/XP


www.level1.com Page 3 of 5

Viewing System Requirements:

Browser: Internet Explorer 6.x or above, Firefox, Chrome, Safari

Cell phone: 3GPP player Real Player: 10.5 or above Quick Time 6.5 or above

Diagram



Order Information

FCS-3101

Package Contents

Power Adapter Mounting Kit Screw Kit Quick Installation Guide

Resource CD (User Manual, Utility, 64-CH Monitoring Software)

No liability or responsibility for any errors or omissions in the content. Specifications are subject to change without notice.

www.level1.com Page 4 of 5

All mentioned brand names are registered trademarks and property of their owners. Copyright © Digital Data Communications GmbH, Germany. All Rights Reserved.

www.level1.com Page 5 of 5