## N-Channel 40V (D-S) MOSFET

These miniature surface mount MOSFETs utilize a high cell density trench process to provide low  $r_{DS(on)}$  and to ensure minimal power loss and heat dissipation. Typical applications are DC-DC converters and power management in portable and battery-powered products such as computers, printers, PCMCIA cards, cellular and cordless telephones.

PRODUCT SUMMARY					
<b>V</b> <sub>DS</sub> <b>(V)</b>	$S_{S}(V)$ $\eta_{DS(on)}(\Omega)$ $I_{D}(A)$				
40	$0.086 @V_{CS} = 10 V$	3.5			
	$0.128 @V_{CS} = 4.5V$	2.9			

- Low r<sub>DS(on)</sub> provides higher efficiency and extends battery life
- Low thermal impedance copper leadframe SC70-6 saves board space
- Fast switching speed
- High performance trench technology

	SC	70-6		$D_{\scriptscriptstyle{1}}$
	Top	View	_	<b>,</b>
D $\square$	1	6	□ D	G₁○──┤ᢜ
DΠ	2	5	D	'
G □	3	4	ш s	$\tilde{S}_{1}$
				N-Channel MOSFET

ABSOLUTE MAXIMUM RATINGS ( $T_A = 25$ °C UNLESS OTHERWISE NOTED)					
Parameter		Symbol	Maximum	Units	
Drain-Source Voltage			40	V	
Gate-Source Voltage			±20	V	
C . D . C . A	T <sub>A</sub> =25°C	T_	3.5		
Continuous Drain Current <sup>a</sup>	$T_{A}=25^{\circ}C$ $T_{A}=70^{\circ}C$	тD	2.9	A	
Pulsed Drain Current <sup>b</sup>			±20		
Continuous Source Current (Diode Conduction) <sup>a</sup>		$I_S$	1.6	A	
D D: : .: a	T <sub>A</sub> =25°C	D_	1.56	W	
Power Dissipation <sup>a</sup>	$T_{A}$ =25°C $T_{A}$ =70°C	тр	0.81	• • •	
Operating Junction and Storage Temperature Range		$T_{J}, T_{stg}$	-55 to 150	°C	

THERMAL RESISTANCE RATINGS					
Parameter	Symbol	Maximum	Units		
M · I · · a	t <= 5 sec	D	100	0000	
Maximum Junction-to-Ambient <sup>a</sup>	Steady-State	$R_{THJA}$	166	°C/W	

1

## Notes

- a. Surface Mounted on 1" x 1" FR4 Board.
- b. Pulse width limited by maximum junction temperature

SPECIFICATIONS (T <sub>A</sub> = 25°C UNLESS OTHERWISE NOTED)							
Demonstra	G 1.1		Limits			TT *4	
Parameter	Symbol	Test Conditions	Min	Тур	Max	Unit	
Static							
Cate-Threshold Voltage	V <sub>GS(th)</sub>	$V_{DS}=V_{GS}$ , $I_D=250$ uA	1			V	
Gate-Body Leakage	$I_{GSS}$	$V_{DS} = 0 V, V_{GS} = \pm 20 V$			±100	nA	
Zero Cate Voltage Drain Current	IDSS	$V_{DS} = 32 \text{ V}, V_{GS} = 0 \text{ V}$			1	uA	
	IDSS	$V_{DS} = 32 \text{ V}, V_{GS} = 0 \text{ V}, T_J = 55^{\circ}\text{C}$			10	uA	
On-State Drain Current <sup>A</sup>	I <sub>D(on)</sub>	$V_{DS}=5V$ , $V_{GS}=4.5V$	10			Α	
D : C O D : A	******	$V_{GS} = 10 \text{ V}, I_D = 3.5 \text{ A}$			86	mΩ	
Drain-Source On-Resistance <sup>A</sup>	fDS(on)	$V_{GS} = 4.5 \text{ V}, I_D = 2.9 \text{ A}$			128		
Forward Tranconductance <sup>A</sup>	gs	$V_{DS} = 10 \text{ V, } I_{D} = 3.5 \text{ A}$		11.3		S	
Diode Forward Voltage	Vsd	$I_S = 1.6 A, V_{GS} = 0 V$		0.75		V	
Dynamic <sup>b</sup>					•		
Total Gate Charge	$Q_{\!\scriptscriptstyle g}$			7.5			
Gate-Source Charge	Qgs	$V_{DS} = 10 \text{ V}, V_{GS} = 4.5 \text{ V}, I_D = 3.5 \text{ A}$		0.6		пС	
Gate-Drain Charge	Qgd			1.0			
Input Capacitance	Gss	N/ -15X/X/ -0X/		720		pF	
Output Capacitance	Coss	$V_{DS} = 15 \text{ V}, V_{GS} = 0 \text{ V},$ f		165			
Reverse Transfer Capacitance	Crss	=1MHz		60			
Turn-On Delay Time	td(on)	$V_{DD} = 10 \text{ V}, R_L = 15 \Omega, I_D = 1 \text{ A}, V_{GEN} = 4.5 \text{ V}$		8		ns	
Rise Time	t <sub>r</sub>			24			
Turn-Off Delay Time	td(off)			35			
Fall-Time	tf			10			

## Notes

- a. Pulse test:  $PW \le 300us duty cycle \le 2\%$ .
- b. Guaranteed by design, not subject to production testing.

Analog Power (APL) reserves the right to make changes without further notice to any products herein. APL makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does APL assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. "Typical" parameters which may be provided in APL data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. APL does not convey any license under its patent rights nor the rights of others. APL products are not designed, intended, or authorized for use as components in systems intended for surgical implant into the body, or other applications intended to support or sustain life, or for any other application in which the failure of the APL product could create a situation where personal injury or death may occur. Should Buyer purchase or use APL products for any such unintended or unauthorized application, Buyer shall indemnify and hold APL and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that APL was negligent regarding the design or manufacture of the part. APL is an Equal Opportunity/Affirmative Action Employer.